PRX SERIES

Professional Channel Mixer



PRX 12
12 Channel Professional Effects Mixer with USB

PRX 16
16 Channel Professional Effects Mixer with USB

PRX 24
24 Channel Professional Effects Mixer with USB

6 Aux
LR / MONO / SUBWOOFER OUT

FEATURES

- High-Quality Editable Dual Effects
- Separate Mono / Subwoofer Output
- Individual +48V Phantom Power
- 4 Group Buses
- 6 Aux Sends

DOUBLE DSP EFFECT | EQ | Bluetooth | USB | MP3

Technical Parameter

Microphone input (MIC Preamplifier)	
Type	XLR, balanced, Separate input circuit
Mic E.I.N.(20Hz- 20kHz)	
@0Ω Source impedance	-134dB/135.7dB A-Weighted
@50Ω Source impedance	-131dB/133.3dB A-Weighted
@150Ω Source impedance	-129dB/130.5dB A-Weighted
Frequency response	<10Hz-150KHz(-1dB) <10Hz-200KHz(-3dB)
Gain range	+10dB ~ +60dB

Maximum input level	+12dBu@+10dB gain
Impedance	About 2.6KΩ balanced
Signal-to-noise ratio	110dB / 112dB A-Weighted (0dBu In @ +22dB gain)
Distortion (total harmonic distortion+noise)	0.005% / 0.004% A-Weighted
Type	6.3mm stereo channel plug, balanced
Impendance	About 20 KΩ balanced 10 KΩ unbalanced
Gain range	-10dB ~ +40dB
Maximum input level	+22dBu@ 0dB gain